



United States - English

My account Cart Where to buy Contact

[PRODUCTS](#) [SHOP](#) [SOLUTIONS FOR](#) [SUPPORT](#) [SERVICES & WARRANTY](#)

Search

[Download Drivers & Software](#) [Diagnose & Fix](#) [Warranty](#) [Product & Parts Detail](#) [User Guides & Manuals](#) [KnowledgeBase & FAQ](#) [Lenovo Services](#)
[Home](#) > [Support](#) > [Product & Parts Detail](#) > Product & Parts Detail

 [My Download List\(0\)](#)

Support

[LOGIN](#) | [Create Support Account](#)
[Download Drivers & Software](#)
[Diagnose & Fix](#)
[Warranty](#)
[Product & Parts Detail](#)
[User Guides & Manuals](#)
[KnowledgeBase & FAQ](#)
[Lenovo Services](#)

Overview - ThinkCentre M55 (type 8808)



Monitor not included

Features and specifications

Processor

- Intel® Celeron® D Processor 336
- Intel® Celeron® D Processor 341
- Intel® Celeron® D Processor 346
- Intel® Celeron® D Processor 351
- Intel® Celeron® D Processor 355
- Intel® Pentium® 4 Processor 531 with HT Technology
- Intel® Pentium® D Processor 820
- Intel® Pentium® D Processor 915
- Intel® Pentium® D Processor 945
- Intel® Core 2 Duo Processor E6300
- Intel® Core 2 Duo Processor E6400

Memory

- 256MB, 512MB, or 1GB
- Supports up to 4GB maximum memory

Hard drive

- 80 GB 7200RPM S-ATA
- 160 GB 7200RPM S-ATA
- 250 GB 7200RPM S-ATA

Graphics

- [Integrated Intel Graphics Media Accelerator 3000](#)

CD and DVD drive

- 48 x CD-ROM
- 16 x DVD-ROM
- 48 x 32x48 x 16x CD-RW/DVD combo
- Multi-Burner Plus 16 x

Networking

- Integrated Broadcom 10/100/1000 (Gigabit) Ethernet

Security

- Chassis intrusion switch (select models)

Operating System

- Microsoft Windows XP Home
- Microsoft Windows XP Professional

ThinkVantage Technologies

ThinkVantage Technologies help our customers become more competitive by delivering industry-leading capabilities that improve productivity and reduce cost. ThinkVantage Technologies includes features such as deployment, backup, security (select models) and more.

Detailed specifications

All specifications for the ThinkCentre M55 type (8808)

Note: Specifications are dependent on the machine type and model

Warranty

- [View warranty status for a machine](#)
- [Warranty information and service upgrades](#)

For additional warranty information, refer to the Statement of Limited Warranty.

System locations, ports, and features

- [Locating front connectors](#)

- [Locating rear connectors](#)
- [System board diagram](#)

Additional product information

- [Troubleshooting](#) - Step-by-step instructions for solving common computer issues
- [Hardware removal and installation](#) - Index for removing or installing options and service parts (text version)

Manuals

- [Hardware Maintenance Manual](#) - Information regarding diagnostics, hardware interfaces, and replacement (FRU) part numbers
- [Hardware replacement guide](#) - Information on removing and replacing customer replacement units (CRUs), including power supply, system board, microprocessor, hard disk drive, memory, and adapter cards
- [User guide](#) - General information including care and setup instructions
- [Safety and Warranty Guide](#) - Information regarding the Statement of Limited Warranty and Safety issues

Service parts

- [System](#)
- [Recovery CD](#)

Country Availability

Available Worldwide

Document ID : PD005666
Last Updated : 19 Sep 2011
Copyright © Lenovo 2011, all rights reserved

Was this page helpful to you? Yes No

{please let us know what you think}

ABOUT LENOVO

- Our Company
- News
- Investor Relations
- Social responsibility
- Legal information
- Jobs at Lenovo
- Articles

SHOP

- Laptops & netbooks
- Tablets
- Desktops & all-in-ones
- Workstations
- Servers
- Accessories & upgrades
- Special offers
- Outlet

SUPPORT

- Download Drivers & Software
- Diagnose & Fix
- Warranty
- Product & Parts Detail
- User Guides & Manuals
- KnowledgeBase & FAQ
- Lenovo Services

RESOURCES

- Where to buy
- Shopping help
- Order status
- Support Phone List
- Blogs & forums
- Product videos
- Training
- Email signup
- Product registration



United States - English

My account | Cart | Where to buy | Contact

PRODUCTS SHOP SOLUTIONS FOR SUPPORT SERVICES & WARRANTY

Search



Download Drivers & Software Diagnose & Fix Warranty Product & Parts Detail User Guides & Manuals KnowledgeBase & FAQ Lenovo Services

Home > Support > Product & Parts Detail > Product & Parts Detail

My Download List(0)

Support

LOGIN | Create Support Account

Download Drivers & Software

Diagnose & Fix

Warranty

Product & Parts Detail

User Guides & Manuals

KnowledgeBase & FAQ

Lenovo Services

Detailed specifications - ThinkCentre M55 (type 6488, 8010, 8792, 8796, 8800, 8804, 8808, 8813)

- Architecture
- Communications
- Expansion
- Power
- Security
- Software
- Storage
- Video

Architecture

System board / Form factor

- Small form factor (2x3) with Intel® Q963 chipset
- Supports Intel® Celeron® D processor with 533MHz FSB and 256KB L2 cache
- Supports Intel® Pentium® D processors with 800MHz FSB with 2x2MB L2 cache
- Supports Intel® Pentium® D processors with 800MHz FSB and 2x1MB L2 cache
- Supports Intel® Core™ 2 Duo processor with 1066 MHz FSB and 2MB L2 cache
- Custom BTX form factor

Note: Hyperthreading is supported only with Microsoft Windows XP Service Pack 1. Hyperthreading must be disabled when using Windows 2000.

Processor

- Intel® Celeron® D Processor 336
- Intel® Celeron® D Processor 341
- Intel® Celeron® D Processor 346
- Intel® Celeron® D Processor 352
- Intel® Celeron® D Processor 356
- Intel® Pentium® 4 Processor 524 with HT Technology
- Intel® Pentium® 4 Processor 531 with HT Technology
- Intel® Pentium® D Processor 820
- Intel® Pentium® D Processor 915
- Intel® Pentium® D Processor 945
- Intel® Core 2 Duo Processor E6300
- Intel® Core 2 Duo Processor E6400

Cache

- 256KB L2 cache - Intel® Celeron® D Processors
- 512KB L2 cache - Intel® Celeron® D Processors
- 1MB L2 cache - Intel® Pentium® 4 Processors
- 2x1MB L2 cache - Intel® Pentium® D Processors
- 2x2MB L2 cache - Intel® Pentium® D Processors
- 2MB L2 cache - Core 2 Duo processors

Chipsets

- Intel Q963
 - Integrated Intel Graphics Media Accelerator 3000
 - Q963 "GF" Northbridge
 - ICH8 Southbridge
 - SMSC 5407 Super IO

IDE controller

- 4 Serial ATA connectors
- No parallel ATA support

Memory

- 400MHz DDR2 (Double Data Rate) dual channel memory support
- PC2-4200 (400MHz) memory supported
- PC2-5300 (400MHz) memory supported
- Two 240 pin DDR2 SDRAM UDIMM sockets
- Supports a maximum memory up to 4GB
- ECC or parity memory is not supported

Audio

- Integrated High Definition (HD) PCI AC'97 2.3 compliant codec
- ADI1983 HD CODEC
- Front - Microphone-in, headphones out
- Rear - Line-in, line-out
- Jack sensing, jack retasking - software will automatically detect which jack the microphone is using.
- Software-based audio (done by processor and ICH8)

Keyboard and mouse

- Preferred Pro full-size keyboard
- USB Optical Wheel mouse

Communications**Networking**

- Integrated Broadcom Gigabit (10/100/1000)

Expansion**Bays**

- One 5.25 inch, half-height 1.6 inch, external access
- One 3.5 inch, slim-line 1 inch, external access, diskette drive (select models)
- One 3.5 inch, slim-line 1 inch, internal access, hard drive

External ports

- Eight USB (two in front, six in back) [Ver 2.0]
- One Ethernet RJ-45
- One serial 9-pin 16550 compatible (select models may have a second serial port)
- One parallel 25-pin parallel (EPP, ECP), IEEE 1284
- Monitor port
- Audio line in, headphone out, and microphone in jacks
- No PS/2 mouse or keyboard connector

Slots

- Slot 1: PCI Express x1
- Slot 2: 32-bit PCI 2.3 (5v)

Power**Power management**

- APM 1.2 and ACPI 2.3

Power supply

- 225 watt supply with variable fan speed
- 110 volt or 220 volt operation controlled by a switch on the back of the unit

Security

- Security chip
- Padlock loop (in rear for optional padlock, Tower only)
- Security slot (in rear for attachment of optional cable lock)
- No keylock
- Power-on password
- Configuration password (administrator password)
- Hard drive password (user and master)
- Boot sequence control
- Boot without keyboard, mouse, or diskette
- USB/Ethernet/serial/parallel/SATA/EIDE/diskette enable or disable
- Disk, removable device, and network device password
- Diskette write protect
- Front USB port disablement
- Cover intrusion switch (select models)

Security chip features:

- Offers platform and user authentication (requires download of security software)
- Executes all private key-related Public Key Infrastructure (PKI) operations right on the chip (requires third party digital certificate, not included)
- Designed to enable secure storage of private keys (requires third party digital certificate)
- Supports industry standard cryptographic interface (MSCAPI and PKCS#11) Provides more secure access authentication by coordinating with Windows logons and strengthening Lotus Notes logons
- Encrypts and decrypts files, folders, and messages with 1024-bit digital signature and up to 256-bit key exchange
- Digital signatures allow non-repudiation and data integrity
- Integrates with optional biometrics and proximity badges
- Adheres to the Trusted Computing Group specification recognized by over 180 companies

Software**Operating system**

- [Microsoft Windows XP Home](#)
- [Microsoft Windows XP Professional](#)

Note: Preloaded software utilizes the [disk-to-disk recovery](#) method. Select models ship without the Operating system.

Storage**Optical drive**

- 48x CD-ROM

- 16x DVD-ROM
- 48x32x48x16x CD-RW/DVD combo
- Multi-Burner Plus 16x

Hard drive features

- 7200RPM Serial ATA supported

Video

Intel Graphics Media Accelerator 3000

- 15-pin VGA output on planar
- Uses Intel Dynamic Video Memory Technology (DVMT)

For models without a separate video card, memory supports both system and video. System memory used by video may be up to 32MB if the system has 128MB installed, up to 160MB if the system has 256MB installed, and up to 256MB if the system has 512MB or more system memory installed, depending on video mode.

Resolution, maximum color depth, and refresh rates

- 640 x 480, 16M colors (120 Hz)
- 800 x 600, 16M colors (120 Hz)
- 1024 x 768, 16M colors (120 Hz)
- 1152 x 864, 16M colors (100 Hz)
- 1280 x 1024, 16M colors (120 Hz)
- 1600 x 1200, 16M colors (120 Hz)
- 1920 x 1080, 16M colors (100 Hz)
- 1920 x 1200, 16M colors (75 Hz)
- 1920 x 1440, 16M colors (85 Hz)

Country Availability

Available Worldwide

Document ID : PD012466
 Last Updated : 01 Jun 2011
 Copyright © Lenovo 2011, all rights reserved

Was this page helpful to you? Yes No

{please let us know what you think}

Submit

ABOUT LENOVO

Our Company
 News
 Investor Relations
 Social responsibility
 Legal information
 Jobs at Lenovo
 Articles

SHOP

Laptops & netbooks
 Tablets
 Desktops & all-in-ones
 Workstations
 Servers
 Accessories & upgrades
 Special offers
 Outlet

SUPPORT

Download Drivers & Software
 Diagnose & Fix
 Warranty
 Product & Parts Detail
 User Guides & Manuals
 KnowledgeBase & FAQ
 Lenovo Services

RESOURCES

Where to buy
 Shopping help
 Order status
 Support Phone List
 Blogs & forums
 Product videos
 Training
 Email signup
 Product registration